Step 1: Open browser (Internet explorer/Chrome) and input the address <u>www.guardingvision.com</u>. And click on "Register" to register for a new account.

		English •
	2	Welcome
Cloud Video		Account/Email
Surveilla	nce	Password
		Forgot Password
00		Login
		Register

Step 2: In the registration page, input the mandatory credentials and select "Email" for registering with email or "Country Code" for registering by a phone number.

User Register	
User Name:	
- Password:	
- Confirm Password:	
Country:	
. Fmail:	
Country Code: Dease choose your country	
Thus choise your country	
Mobile Phone Number:	
CARICHA Code:	

Step 3: Once the account is created, select "Device Management" and select "Add" to add a new device.

252	Device Management				berree bornan	Aud
Device Management	Alias	Device Domain	Device Serial No.	IP/Port No.	Status	Device Operation
දරූ	NVR516P16-K2(746017023)	746017023	746017023	47.188.176.14/80	Online	/ 🖻 🖻 🧐
thers' Shared Devices						
_						
28						
My Shared Devices						
20						
My Account						

Step 4: In the "Add Device" pop-up window, input the device serial number (Last 9 digits of the serial number found on the device sticker) and click on "Search".

2023	Device Walla	gement					Add
vice Management		Alias	Device Domain	Device Serial No.	IP/Port No.	Status	Device Operation
	NVR516	Add Device					
		Device Serial No.:	123456789		Search		
					Cancel		

Step 5: If the platform access is enabled on the device, then you should see the device on the "Add device" window. Click on the '+' icon for the device. Click on the link for Enabling "Platform Access"

https://app.box.com/s/ftj2keo6pvvvkpif9ukquyp7jrvhktwx.



Step 6: Enter the verification code found on the platform access page of the device. Click "Add".

tộ:	Device Mana	gement					Q O Add
		Alias	Device Domain	Device Serial No.	IP/Port No.	Status	Device Operation
	NVR516	Add Device					
		Device Serial No.:	204135010		Search		
		Verification Code:			]		
					Cancel Add		

Step 7: Click "OK". Now the device should be added into the Guarding vision account. To view video stream, download the Guarding vision ass on your mobile phone and login with the account credentials just created.

		Add Device				
<b>\$</b>	Device Man				Device Domain	Q Add
Device Management			Added.		Status	Device Operation
	NVR51	*Alias:	CAM-IP-HK4PTZ(204135010)		Online	
		*Device Domain:	204135010	?		
		Device Serial No.:	204135010			
		UPnP Mode:	Auto Manual			
		Select auto mode as default it fails, select manual mode.	, and the system gets the port num	ber. from the device. If		
		Server Port Number:				
		HTTP Port Number:				
				Cancel		

CAM-IP-HK4PTZ(204135010) 204135010 204135010 47.188.176.14 Online		
	1	t 🗅 🤫
thers' Shared Devices NVR516P16-K2(746017023) 746017023 746017023 47.188.176.14/80 Online		i la «
20		
My Account		

## Sharing the device:

To share the device with another Guarding vision account, click on the "Share" icon next to the device name

5	Device Management			Device Serial No.,	Device Domain	Q S Add
Device Management	Alias	Device Domain	Device Serial No.	IP/Port No.	Status	Device Operation
	CAM-IP-HK4PTZ(204135010)	204135010	204135010	47.188.176.14	Online	/ in 1a <
thers' Shared Devices	NVR516P16-K2(746017023)	746017023	746017023	47.188.176.14/80	Online	/ 🖻 🖻 🤫
My Account						

Select "Email" for sharing by email or select "Mobile Phone Number" to share by mobile number. Click on the check mark next to the device and click "Share".

nare with:		
• Email:	example@gmail.com	History
Mobile Phone Number:	Country Code + Phone No.	
Remark:		Share
	125010)	•
	135010)	
CAM-IP-HK4PTZ(20		•